DIGITAL LUX/LIGHT METER LX-1330B



Future:

- Measures 0-200,000 Lux for a wide range of use, ideal for architects,
 - lighting designers or photograph hobbyists
- Separate light sensor allows to take measurement at an optimum position
 - Auto zero adjustment, high accuracy
 - Displays in lux or fc
 - (1fc = 10.76Lux)
 - Data hold and Peak hold
 - · Low battery indication

Technical specifications:

Range: 200/2,000/20,000/200,000 Lux

• 20/200/2,000/20,000 fc

Accuracy: (3.0%~5.0%)

Resolution: 0.1Lux, 0.01fc

Response time: 0.5s

Dimensions: 79x160x43mm

Battery: 9Vx1, 6F22

Sensor: silicon photo diode with filter

Repeatability: 2%

Temperature characteristic: 0.1%/

